

6150RF

Fixed Language Integrated Keypad/Transceiver

Add wireless technology to any installation with Honeywell's 6150RF keypad. It offers the unbeatable combination of attractive, convenient features and competitive value in a single, quick-install package. The integrated design solves even the trickiest installation challenges and reduces costs by letting you add full wireless capability to any compatible VISTA™ control—without additional wiring or sacrificing zones.

Dealers can add the 5828 and 5828V wireless keypads to VISTA for the first time, presenting a tremendous upsell opportunity by letting them offer their customers secondary wireless keypads on every installation with virtually no install time.



With Door Attached



Without Door

FEATURES

- 6150 Fixed Language Keypad
- Built-in 16-Zone wireless transceiver
- Compatible with 5828 and 5828V wireless keypads
- Single four-wire run is all that's required
- It is the ideal choice where wireless keys are to be used:
 - Keys can be programmed at the panel, just as they would with the 5881ENM*
 - Keys can be enrolled locally at the keypad, without taking up additional zones at the control
- Fully compatible with all 5800 wireless devices including bidirectional
- On-board single relay provides a low cost solution for opening garage doors.

STYLISHLY DESIGNED

- Sleek white design blends with any décor
- Contoured, removable door lets customers customize the keypad for the look they want
- With the door closed the keypad has a smooth, unobtrusive appearance

EASY TO OPERATE

- The Fixed Language display is easy to read, with large characters and simplified descriptions
- The sounder beeps to help identify security system status
- Comfortable soft-touch keys labeled with simple commands are illuminated for nighttime visibility
- Four larger function keys can be programmed for one touch operation and are accessible even when the door is closed

* 5881ENM is not available in Canada
Wi-Fi® IEEE 802.11
B/G/N radio

6150RF

Fixed Language Integrated Keypad/Transceiver

SPECIFICATIONS

DIMENSIONS

- 4-7/8" H x 6" W x 1" D
(125mm x 160mm x 25 mm)

SOUNDER

- Piezo Electric

WIRING

- - (Black): Ground
- + (Red): +12 VDC (Aux. Power)
- D1 (Green): "Data In" to control panel
- D0 (Yellow): "Data out" from control panel

CURRENT

- Standby: 80ma
- Activated: 105ma

ORDERING

6150RF	Fixed Language Keypad with Integrated Transceiver – English
6150FFR	Fixed Language Keypad with Integrated Transceiver – French
5828	Wireless Fixed English Keypad
5828V	Wireless Fixed English Keypad with Voice

For more information

www.honeywell.com/security

Honeywell Security and Fire

2 Corporate Center Dr. Suite 100
P.O. Box 9040
Melville, NY 11747
1.800.323.4576
www.honeywell.com

L/6150RFD/D | 12/16
© 2016 Honeywell International Inc.

Honeywell